

INTELLIGENT CONTROLLERS

SHOW DESIGNER II

1024 DMX Channels, (3&5 Pin Outputs)
 48 fixtures up to 32 channels each
 Large DMX Fixture library
 Effects Engine with 48 Factory chases
 1152 Programmable Chases
 4752 Programmable Scenes
 1152 Programmable Shows
 1152 Programmable Presets
 8 Faders allow for control of up to 32 DMX channels per fixture and scene masters.
 48 Fixture Groups
 Scene Preview with "Go" feature
 Factory ready Color, Gobo, Focus & Effect Presets
 Controller comes "Tabletop Style"—Includes removable rubber rails to fit standard 19-inch rack mount

FRONT PANEL

80 Character backlit LCD Display for easy programming
 4 x Menu and control data wheels
 PAN/TILT Joystick
 48 Multi function Quick access buttons
 8 Faders x 4 banks
 XLR light connector
 On/Off Power switch

REAR PANEL

2 x (3 Pin) DMX Outputs
 2 x (5 Pin) DMX Outputs
 Midi-In & Out ports
 3.5" Disk drive (Show Designer 2D version only)
 Keyboard Input (Show Designer 2D version only)
 RS-232 Port, for PC interface
 2 x DMX Polarity Switches per output (3 Pin Outs Only)
 RCA Audio input for Chases

TECHNICAL SPECS AND DATA

Polarity switch (2-,3+ / 2+, -3-) 3 Pin XLR only
 1 MB memory
 Battery back up
 19" rack mountable, 6 space
 Dimensions: 19" x 10.5" x 4"
 Weight: 10 lbs
 Voltage: 120V/220V (9-12v DC / 1200ma)



Computer keyboard not included.



SHOW DESIGNER 2D

Same features as the Show Designer II
 Includes 3.5" PC Floppy Disc Drive on rear
 Includes PS-2 keyboard input



SHOW DESIGNER UPDATE CABLE
 Model # SD-DC



DVD
 Instructional DVD available.